

NetworX NX8E Addendum

Checksum 7354 dated 26-June-2002

I. PROGRAMMING CHANGES

I.A. *Features*

1. Added *NIGHT* mode support for the NX1208E LED keypads and NX1248E LCD keypads. In this mode the NX8E will bypass all zones that have the Entry Guard enabled.

Location 23	Segment 2	Option 8	Manual pages 17, 47
	On enables <i>INSTANT</i> mode toggle		

Location 23	Segment 4	Option 3	Manual pages 17, 47
	ON disables the door delays in <i>NIGHT</i> mode		

2. Added CLEAN ME feature

Location 37	Segment 6	Option 6	Manual pages 22, 49
	On disables the <i>CLEAN ME</i> report		

I.B. *Zone Configurations*

Location 111	Segment 4	Option 3	Manual pages 32, 58
Access Control	Works in conjunction with Access Control module to delay alarm activation for 60 seconds. NOTE: Do not enable this option unless configured with Access Control module.		

Location 111	Segment 4	Option 4	Manual pages 32, 58
Request to Exit Zone	Works in conjunction with Access Control module to cause this zone to act as a <i>request to exit</i> input. Enabling this option will disable it for alarm activation.		

I.C. *Auxiliary Output Events*

Added following events:

69	Forced Door Alarm
70	Forced Door Restore